



## 100 MHz Drop In Bandpass Filter

This Drop-In style bandpass filter is available in a wide range of octave bandwidths from 17.5 MHz to 530 MHz. The filter exhibits 1.5dB Max. insertion loss across the passband with 50dBc attenuation at 16% from band edge.

Overall size is 1.80" x .40" x .40" with .015" diameter RF Pins and 0-80 mounting holes on bottom of the unit.

Eastern Wireless TeleComm, Inc.